



ul. Konstytucyjna 79/81  
95-200 Pabianice  
tel/fax 48 42 2270971 POLAND  
e-mail: fif@fif.com.pl

## PK-1P 230V ELECTROMAGNETIC RELAY



www.fif.com.pl

F&F products are covered by an 24 months warranty from date of purchase

### PURPOSE

Electromagnetic relay in single-module casing intended for direct assembly on the rail TH-35.

### FUNCTIONING

Application of the supply voltage to the coil of relay will cause switch joints in positions 11-12. This is indicated by shine a green LED. After the outage, the power joints back in positions 11-10.


### ASSEMBLY

1. Take OFF the power.
2. Put on relay on the rail in the switchgearbox.
3. Connect to system with wiring diagram

### TECHNICAL DATA

standard no.	IEC 61095
supply	230V AC
connection current	$I_e=16A$
heat current	$I_m=16A$
connection voltage	$U_c=250V$
joints	1P
usage category	AC-7a
isolation voltage	400V
voltage surge resistor	joint-coil 2.5kV
separate current circuits	3.6kV
joint gap	1.2kV
pollution level	3
safety label	B16(16A)
overvoltage capacity	3kV
coil voltage	$U_c=12V AC/DC$
voltage of control circuit	$U_s=12V AC/DC$
security sign	B
protection level	IP20
activation time	max. 40ms
turn-off time	max. 20ms
mechanical life	min $5 \times 10^6$ cycles
current consumption	25mA
voltage indicator	LED
connection	screw terminals 2.5mm <sup>2</sup>
working temperature	-25+50°C
dimensions	1 module (18mm)
fixing	on the rail TH-35

### WIRING DIAGRAM



A090805